


How to restore or import Factory Default Presets

The easiest way to restore all factory presets and settings is to use the 'Restore Factory Default Settings' function in the SYSTEM -> Reboot tab:



However, **this will delete all user settings and presets**

and is not very convenient in many applications.

With the Factory Default Presets file provided in the firmware package, it is very simple to selectively import only certain presets while preserving all user preset data and settings. The following step by step instructions will guide you through the import process.


As an example the D*AP4 VAP EDITION Input section is shown, but the process is identical in the web UI of all other current slim line devices.

1. Go to the required section in the D*AP web UI (Input section shown) and click the 'Import' button in the PRESETS section


The screenshot displays the D*AP web interface. At the top, there are several meters for M1, M2, V1, V2, 2L, 2R, and four numbered meters (1, 2, 3, 4). Below the meters is a navigation bar with tabs for SYSTEM, INTERFACES, ROUTING, AUDIO PROCESSOR, and MEASUR. The 'Input' tab is selected. The main content area shows a 'Voice' section on the left with a 'Program' dropdown. The 'ON AIR' section is highlighted with a red border and contains a 'Program' dropdown, a 'Linked' dropdown, a '2L/2R' checkbox (checked), an 'Input Mute' checkbox (unchecked), an 'Input Gain (dB)' field (0.0), an 'L/R Stereo' dropdown, two 'OFF' buttons, and two '0' fields. The 'PRESETS' section contains a 'Mono Input' dropdown, a 'Linked' dropdown, a '2L/2R' checkbox (checked), an 'Input Mute' checkbox (unchecked), an 'Input Gain (dB)' field (0.0), an 'L+R Mono' dropdown, two 'OFF' buttons, and two '0' fields. At the bottom of the 'PRESETS' section, there are four buttons: 'export', 'import', 'copy', and 'paste'. A blue arrow points to the 'import' button.

- 2. A dialog box will open. Browse for the *_Factory_Default_Presets.xml file from the firmware package


Please note: * is a place holder for whatever device type you are using (D*AP4, D*AP8...)



- 3. Select the Preset you would like to import



4. Select 'Create additional Settings' to preserve any existing presets of the same name



5. Click 'Save'
6. Repeat these steps to import all necessary presets

The *_Factory_Default_Preset.xml file contains all default Presets, Events and Actions.

Events and Actions can be imported with the same principle, while the event import dialog even allows for batch imports. When importing Events or Actions, all necessary Presets will be restored automatically.